


Cleaning soldering iron Oxidized black layer



Extend the service life of soldering iron



Quick
cleaning



Soldering iron Repair cream



Clean the blackened oxide layer



One step repair Old soldering iron



Restore blade brightness and Tin planting ability



Before repair



After repair

Product advantages

...



Easy to operate



Remove oxide layer



Repair and maintenance



Recycling

Product parameters



Name:

Solder Iron Repair Cream

G.W.:

8g, 20g, 30g

Purpose:

Repair soldering iron head

Size:

43mm * 48mm(30g)

38mm * 18mm(20g)

29mm * 15mm (8g)



*The above dimensions are manually measured,
If there are slight differences, please refer to the actual situation



3

Clean the soldering iron with a cleaning sponge



4

Plating a new tin layer to rejuvenate the soldering iron

Revival soldering iron

Operating Steps



• • •

Four steps to clean the soldering iron head

4

1



Heat the soldering iron to 300 °C -360 °C

2



Let the soldering iron tip repeatedly rub against the repair paste

